7. Electrical Parts List

7-1 DW21G5VD3X/BWT

You can search for the updated part code through ITSELF web site.
URL : http://itself.sec.samsung.co.kr

ASSY CHASSIS

Level	Loc. No.	Code No.	Description ; Specification	Remark
1		AA91-06065A	ASSY CHASSIS;DW21G5VD3X/BWT,VC1A,RUSSIA	S.N.A
2	PCB+HC	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
2		AA95-01758X	ASSY SUB-PCB CRT;DW21G5VD2X/SPL,VC1A, ,	
3	IC501	AA96-50311E	ASSY H/S;-,-,AA62-30175D,TDA6108JF,-	S.N.A
4		1201-001330	IC-VIDEO AMP;6108,ZSIP,9P,-,SINGLE,-,PLA	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-30175D	HEAT SINK-PS;-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
⚠ 3	V999S	3704-001105	SOCKET-CRT;11P,20PI,26.5PI,NI,-	
3	WCN501	AA39-20030G	LEAD CONNECTOR-ASSY;,8P,200MM,67096-008,	
3	WCN502	AA39-20029A	LEAD CONNECTOR-ASSY;,7P,200,67096-007,S,	
3		AA97-05587A	ASSY AUTO-SUB;DW21G5VD2X/SPL,VC1A	S.N.A
4	C504	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X5	
4	C505	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
4	C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m	
4	C507	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
4	C508	2301-001259	C-FILM,MPPF;100nF,5%,400V,TP,19x8x16,7.5	
4	CN501A	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
4	CN502A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
4	D501	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D502	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D503	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
4	D504	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
4	EL701	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EL702	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	GT501	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT502	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT503	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	L501	2701-000002	INDUCTOR-AXIAL;100uH,10%,4.2x9.8mm	
4	PCB	AA41-00318A	PCB-CRT;SMD-21G5,FR-1,1L,A,1.6T,330x245,	S.N.A
4	R501	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R502	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R503	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R504	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R505	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R506	2001-001102	R-CARBON(S);200OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R507	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R508	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R509	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
4	R510	2003-000540	R-METAL OXIDE(S);1Kohm,5%,2W,AF,TP,4x12m	
4	R511	2001-000096	R-CARBON(S);1MOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R512	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
4	R513	2008-000290	R-FUSIBLE(S);2.4ohm,5%,2W,AF,TP,3.9x10mm	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
2		AA95-01783E	ASSY SUB-PCB,A/V FRONT;DW21G5VDX/SPL,VC1	
3	CNM711	AA39-00070A	LEAD CONNECTOR-ASSY;,4P,200MM,YBNH250-04	
3	JAC701	3722-001031	JACK-PIN;3P,3.6mm,#18,AU	
3	JAC702	3722-000143	JACK-PHONE;1P(VER),3.4PI,AG,BLK,NO	
3	WCNM70	AA39-20461D	LEAD CONNECTOR-ASSY;,11P,600MM,YBNH250-1	
3	WCNM71	AA39-20069F	LEAD CONNECTOR-ASSY;,5P,600MM,67096-005,	
3		AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A
3		AA97-07110A	ASSY AUTO-A/V FRONT;SMD-21G5,V16A,AA95-0	S.N.A
4	CM50	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	CM51	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	CM52	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	CM53	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	LM50	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	LM51	2001-000309	R-CARBON;110OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	LM52	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	LM53	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	LM54	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	LM55	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	PCB	AA41-00354B	PCB-AV;SMD-21G5,FR-1,1L,B,1.6T,245x245,V	S.N.A
4	RM50	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
4	RM51	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
2		AA95-01822D	ASSY SUB-PCB,MASTER;DW21G5VD2X/SPL,VC1A,	
3	CN801	AA39-20179A	LEAD CONNECTOR-ASSY;,3(2)P,300MM,YFH800-	
⚠ 3	SW811S	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,JPW-2104B	
3		AA97-05250A	ASSY AUTO-SUB;DW21G5,C16A,PAL	S.N.A
4	EY801	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY802	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY803	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY804	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	GT01A	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT02A	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT03A	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT801	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	PCB	AA41-00355A	PCB-MASTER;DW21G5,FR-1,1L,A,1.6T,245x245	S.N.A
3		AA61-10320A	BRACKET-MASTER;T3350,SECC,T1.0,-,-,-,-	S.N.A
3		6001-000057	SCREW-MACHINE;RH,+,M3,L6,ZPC(BLK),SWRCH1	S.N.A
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
2		AA95-01828A	ASSY SUB-PCB,OPTICAL;SMD21G5S,VC1A,NTSC,	
3	CN004A	AA39-00100F	LEAD CONNECTOR-ASSY;,4P,200MM,YBNH250-04	
3	JKD501	3707-001005	CONNECTOR-OPTICAL;PLUG,SM,-,4.4/2.0MM	
3		AA97-05510A	ASSY AUTO-SUB;SMD21G5S,VC1A,NTSC	S.N.A
4	CD521	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
4	CD522	2202-000127	C-CERAMIC,MLC-AXIAL;10nF,+80-20%,25V,Y5V	
4	GTD02	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	PCB	AA41-00591A	PCB-OPTICAL&COAXIAL;DW21G6,FR-1,1L,A,1.6	S.N.A
4	RD538	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
2		AA95-03136A	ASSY SUB PCB-UMI;DW21G5VD3X/BWT,VC1A,RUS	
3	C229	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,	
3	CN001	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
3	CN002	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
3	CN003	3711-003495	CONNECTOR-HEADER;NOWALL,34P,2R,2.54MM,AN	
3	CN004	AA39-00307A	LEAD CONNECTOR-ASSY;DW21G6VD2,UL1007#26,	
3		AA97-13684A	ASSY AUTO-UMI;DW21G5VD3X/BWT,VC1A,RUSSIS	N.A
4	C216	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C220	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
4	C223	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5	
4	C231	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
4	C232	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C235	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C236	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C238	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
4	C239	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
4	C240	2305-000196	C-FILM,MPEF;150nF,5%,63V,TP,-,5mm	
4	C242	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C246	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C249	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C250	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C604	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C610	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C611	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C612	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C613	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C614	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C615	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C616	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C618	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C619	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C620	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C623	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	

Loc. No.		Code No.	Description ; Specification	Remark
4	C624	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C625	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C627	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
4	C631	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	C633	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C901	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C905	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
4	C906	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C907	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	
4	C910	2401-003102	C-AL;100uF,20%,10V,GP,TP,5x11,5	
4	C912	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C913	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm	
4	C915	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	L201	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L203	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L204	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L205	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L206	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L601	2702-001100	INDUCTOR-RADIAL;3.9uH,10%,4x6mm	
4	L602	2702-001100	INDUCTOR-RADIAL;3.9uH,10%,4x6mm	
4	L603	2702-001100	INDUCTOR-RADIAL;3.9uH,10%,4x6mm	
4	L901	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	L902	2702-001094	INDUCTOR-RADIAL;10uH,10%,6x4mm	
4	Q202	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q901	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	XT601	2801-000186	CRYSTAL-UNIT;18.432MHz,25ppm,28-AAM,8pF,	
4	XT901	2801-003750	CRYSTAL-UNIT;8MHZ,30PPM,28-AAA,22PF,80OH	
4	XT902	2801-003433	CRYSTAL-UNIT;12MHZ,30PPM,28-AAM,30PF,30O	
4		AA97-13683A	ASSY SMD-UMI;DW21G5VD3X/BWT,VC1A,RUSSI	S.N.A
5	C218	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C219	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
5	C221	2203-000891	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
5	C222	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C226	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C227	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C233	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C234	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C237	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C241	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	C243	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C244	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C245	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C247	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
5	C248	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C601	2203-001077	C-CERAMIC,CHIP;0.056nF,5%,50V,NP0,TP,201	
5	C602	2203-001077	C-CERAMIC,CHIP;0.056nF,5%,50V,NP0,TP,201	
5	C603	2203-001077	C-CERAMIC,CHIP;0.056nF,5%,50V,NP0,TP,201	
5	C605	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	C606	2203-000701	C-CERAMIC,CHIP;0.002NF,0.25PF,50V,C0G,TP	
5	C607	2203-000701	C-CERAMIC,CHIP;0.002NF,0.25PF,50V,C0G,TP	
5	C609	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	C617	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	C621	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C622	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C626	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C628	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C629	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C630	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
5	C632	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	C634	2203-000938	C-CERAMIC,CHIP;0.47NF,5%,50V,C0G,TP,2012	
5	C902	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
5	C903	2203-000634	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,201	
5	C904	2203-000634	C-CERAMIC,CHIP;0.022NF,5%,50V,C0G,TP,201	
5	C908	2203-001002	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,201	
5	C909	2203-001002	C-CERAMIC,CHIP;0.047NF,5%,50V,C0G,TP,201	
5	C911	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
5	C914	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP,	
5	D901	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	
5	IC601	1204-001925	IC-SOUND PROCESSOR;MSP3411G-B8,PLQFP,64P	
5	IC901	AA09-00305A	IC MICOM;UPD78F0034AGC-580-8B,SNM-746,64	
5	IC902	AA97-13675A	ASSY MICOM;,VC1A,TDA9394H/N1/5,SPM-746CS	
6	IC902	AA09-00239A	IC MICOM;TDA9394-OTP,80,3.3V&8V,12MHZ,UO	
5	PCB	AA41-00524C	PCB-U.M.I;SMD-21G5S,FR-4(UV),2L,C,1.6T,1	S.N.A
5	Q203	0501-002049	TR-SMALL SIGNAL;BC858,PNP,310mW,SOT-23,T	
5	R211	2007-000092	R-CHIP;15Kohm,5%,1/16W,DA,TP,1608	
5	R213	2007-000097	R-CHIP;47Kohm,5%,1/16W,DA,TP,1608	
5	R215	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	

Loc. No.		Code No.	Description ; Specification	Remark
5	R216	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R217	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R218	2007-000828	R-CHIP;39Kohm,1%,1/16W,DA,TP,1608	
5	R219	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
5	R220	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R221	2007-000102	R-CHIP;100Kohm,5%,1/16W,DA,TP,1608	
5	R222	2007-000129	R-CHIP;27Kohm,5%,1/16W,DA,TP,1608	
5	R223	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R225	2007-000082	R-CHIP;3.3Kohm,5%,1/16W,DA,TP,1608	
5	R226	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R227	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R228	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R229	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R230	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R231	2007-000075	R-CHIP;220ohm,5%,1/16W,DA,TP,1608	
5	R232	2007-000106	R-CHIP;220Kohm,5%,1/16W,DA,TP,1608	
5	R233	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R234	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R235	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R236	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	R237	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	R238	2007-000070	R-CHIP;0ohm,5%,1/16W,DA,TP,1608	
5	R601	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R602	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R603	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R604	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R606	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R607	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R608	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R609	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R610	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R611	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R612	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R613	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R614	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R615	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R616	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R617	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R620	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R901	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R902	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R903	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R904	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R905	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R906	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R907	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R908	2007-000072	R-CHIP;47ohm,5%,1/16W,DA,TP,1608	
5	R909	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R910	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R911	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R912	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R913	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R914	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R915	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R916	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R917	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R918	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R919	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R920	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R921	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R922	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R923	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R924	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R925	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R926	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R927	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R928	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R929	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R930	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R932	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R933	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R934	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R935	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R936	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R937	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R938	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R939	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	

Loc. No.		Code No.	Description ; Specification	Remark
5	R940	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R941	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R942	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R943	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R944	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R946	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R947	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R948	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	R949	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R950	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R951	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R952	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R953	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R954	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R955	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R956	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R957	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R958	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R959	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R960	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R961	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R962	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R963	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R964	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R965	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R966	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R967	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R968	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R969	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R970	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R971	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R972	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R973	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R974	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R975	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R976	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R977	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R978	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R980	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R982	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R983	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R984	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R985	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R986	2007-000084	R-CHIP;4.7Kohm,5%,1/16W,DA,TP,1608	
5	R988	2007-000124	R-CHIP;2.2Kohm,5%,1/16W,DA,TP,1608	
5	R989	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R990	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R991	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R992	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R993	2007-000074	R-CHIP;100ohm,5%,1/16W,DA,TP,1608	
5	R994	2007-000078	R-CHIP;1Kohm,5%,1/16W,DA,TP,1608	
5	R995	2007-000090	R-CHIP;10KOHM,5%,1/16W,DA,TP,1608	
5	ZD202	0403-000620	DIODE-ZENER;RLZ5.6B,5.6,500mW,LL-34,TP	
5	ZD901	0403-001284	DIODE-ZENER;RLZ3.3A,3.16-3.38V,500MW,LL-	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A
⚠ 2		AA96-20109B	ASSY POWER CORD;-,CP2/NO(4.0),H/C250,KKP	S.N.A
3		3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
3		AA39-10006X	CBF POWER CORD;-,KKP419C,KLCE-2F,2.286MT	
3		AA61-20284A	HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
2		AA95-01753A	ASSY SUB-PCB CONTROL;DW21G5DV2,VC1A,AA95	
3	CND703	AA39-00116D	LEAD CONNECTOR-ASSY;VC1A,UL1007#26,UL/CS	
3	CND704	3711-001128	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,ANGLE,S	
3	CND74A	AA39-00159B	LEAD CONNECTOR-ASSY;,8P,TUBE,800/780MM,5	
3	LDD701	0601-000385	LED;ROUND,RED,3mm,700nm	
3	LDD71A	AA61-50044A	GUIDE-LED;-,ABS,-,-,-,BLK,V0,AIWA	S.N.A
3	RMD701	AA32-00012A	MODULE REMOCON;ORC-50HF2,38KHZ,940NM,MES	
3	SWD701	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD702	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD703	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD704	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD705	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD707	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD708	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD709	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD710	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	
3	SWD711	3404-000176	SWITCH-TACT;12V,50mA,120gf,6x6mm,SPST	

Loc. No.		Code No.	Description ; Specification	Remark
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-05512A	ASSY AUTO-SUB;SMD21G5S,V16A	S.N.A
4	0	AA41-00527B	PCB CONTROL;VC1A,FR-1,1,VER.01,1.6,330*2	S.N.A
4	CD701	2401-002291	C-AL;47uF,20%,16V,GP,TP,6.3x5,5	
4	CD702	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
4	DD701	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DD702	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	QD701	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	RD701	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD702	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	ZDD701	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
4	ZDD702	0403-000510	DIODE-ZENER;MTZJ6.2B,6.2V,5.96-6.27V,500	
3		AA61-00586B	HOLDER-TOP;15X5,ABS,-,-,-,BLK,HB	S.N.A
3		6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
2		AA61-00483C	HOLDER-CHASSIS;21G5,HIPS V0,-,-,-,G4309,	S.N.A
2		AA94-12494A	ASSY PCB MISC-INTERFACE;,VC1A,	
3	CND01	3711-004945	CONNECTOR-HEADER;BOX,30P,2R,2.54MM,STRAI	
3	CND02	3708-001364	CONNECTOR-FPC/FFC/PIC;35P,1.25MM,STRAIGH	
3	CND03	AA39-00342A	LEAD CONNECTOR;VC1A,UL1007#26,UL/CSA,8P,	
3	CND04	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
3	CND05	AA39-00229A	LEAD CONNECTOR-ASSY;,5P,100MM,35023-0005	
3	CND06	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
3	CND07	3708-001696	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S	
3	CND08	3708-001695	CONNECTOR-FPC/FFC/PIC;13P,1MM,STRAIGHT,S	
3	CND09	3708-001696	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S	
3	CND10	3708-001695	CONNECTOR-FPC/FFC/PIC;13P,1MM,STRAIGHT,S	
3		0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3		AA97-13669A	ASSY AUTO-I/F;,VC1A	S.N.A
4	BDD501	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	BDD502	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	CD101	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD102	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD103	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD104	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD301	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
4	CD302	2401-002042	C-AL;220uF,20%,10V,GP,TP,6.3x11,5	
4	CD303	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD304	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	CD305	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	CD307	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	CD308	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
4	CD501	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	CD502	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
4	CD503	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
4	CD505	2401-000913	C-AL;22uF,20%,16V,GP,TP,5x11,5	
4	CD506	2202-000632	C-CERAMIC,MLC-AXIAL;100nF,20%,50V,Z5U,TP	
4	CD507	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
4	CD508	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
4	CD509	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
4	CD510	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
4	CD511	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
4	CD512	2201-000558	C-CERAMIC,DISC;0.47NF,10%,50V,Y5P,TP,5X3	
4	CD517	2401-000416	C-AL;10uF,20%,16V,GP,TP,5x11,5	
4	CD518	2401-000416	C-AL;10uF,20%,16V,GP,TP,5x11,5	
4	DD502	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DD503	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DD504	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	DD505	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4	FLD501	2901-001125	FILTER-EMI ON BOARD;50V,0.5A,-,220pF,7x2	
4	GTD01	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	LD501	2701-000112	INDUCTOR-AXIAL;100uH,10%,3x7mm	
4	LD502	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	QD501	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
4	QD502	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
4	QD601	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
4	QD602	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
4	RD301	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD302	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD303	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD504	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD505	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD506	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD507	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD508	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD509	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD510	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark
4	RD511	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD512	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD513	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD514	2001-000490	R-CARBON;2000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD515	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD516	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD517	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD518	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD519	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD520	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD521	2001-000490	R-CARBON;200OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD522	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD523	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD524	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD525	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD526	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD527	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD528	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD534	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD535	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD536	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD537	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD539	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
4	RD602	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD603	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD604	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD605	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD606	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4	RD607	2001-000281	R-CARBON;1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
4		AA97-13670A	ASSY SMD-I/F;,V18B	S.N.A
5	0	AA41-00847B	PCB SUB-INTERFACE;VC1A ALL,FR-1,1L,B,1.6	S.N.A
5	ICD302	1201-001419	IC-VIDEO AMP;7660,SSOP,16P,173MIL,TRIPLE	
5	ICD501	1002-001241	IC-D/A CONVERTER;AK4382VT,24BIT,TSSOP,16	
5	ICD502	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
5	ICD503	0801-000442	IC-CMOS LOGIC;74HCU04,INVERTER,SOP,14P,1	
2		AA94-12520A	ASSY PCB MAIN;DW21G5VD3X/BWT,VC1A,RUSSIA	
3	C806	2401-003030	C-AL;220uF,20%,450V,GP,BK,30x35,10	
3	CN301	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5-,NYLON66	S.N.A
3	CN701	3711-000628	CONNECTOR-HEADER;BOX,11P,1R,2.5MM,STRAIG	
3	CN705	3711-004945	CONNECTOR-HEADER;BOX,30P,2R,2.54MM,STRAI	
3	CN706	3711-003974	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
3	CN707	3711-003051	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGH	
⚠ 3	CR401S	2306-000357	C-FILM,MPPF;8.2nF,5%,1.6KV,BK,20x9.5x17.	
⚠ 3	CR405S	2306-000195	C-FILM,MPPF;360nF,5%,400V,TP,26x19x11.5,	
⚠ 3	CX801S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 3	CX802S	2306-000318	C-FILM,MPPF;220nF,20%,250V,TP,-,22.5mm	
⚠ 3	CY801S	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
⚠ 3	D414	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	
⚠ 3	D801S	0402-001082	DIODE-BRIDGE;RBV406LFB,600V,4A,-	
⚠ 3	D805	AA96-00243D	ASSY H/S;-,BRIDGE,AA62-00045A,D06U20S,DR	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		0402-001374	DIODE-RECTIFIER;FFPF06U20S,200V,6A,TO-22	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
⚠ 3	FP801S	3601-000281	FUSE-CARTRIDGE;250V,4A,TIME-LAG,GLASS,5.	
3	IC301	AA96-00623A	ASSY H/S;-,POWER,AA62-00056A,LA7845	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		1204-000517	IC-VERTICAL DEF.;LA7845,SIP,7P,-,PLASTIC	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00056A	HEAT SINK-PS;-,-,T1.0,-,41*35*70,D2,-,-,	S.N.A
3	IC601	AA96-00623B	ASSY H/S;-,SOUND,AA62-00056A,TDA7266S,VC	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		1201-001308	IC-POWER AMP;7266,ZIP,15P,-,DUAL,26dB,PL	
4		6003-000334	SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
4		AA62-00056A	HEAT SINK-PS;-,-,T1.0,-,41*35*70,D2,-,-,	S.N.A
⚠ 3	IC801S	AA96-50373J	ASSY H/S;-,POWER,AA62-30181K,5Q0765R,21	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		1203-001932	IC-PWM CONTROLLER;5Q0765,TO-220F,5P,185M	
4		6003-000333	SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
4		AA62-30181K	HEAT SINK-ES;-,AL6063 EXTR.,2,WHT,40MM,-	S.N.A
3	IC902	1103-001213	IC-EEPROM;M24C16-WBN6,2048x8Bit,SDIP,8P,	
3	JA701	3722-000195	JACK-SCART;42P,-,SN,BLK,NO	
3	L405	AA27-00025A	COIL CHOKE;-,1MH,10%,-,-,BK,-,12X20,14X2	
⚠ 3	LR401S	AA27-00160A	COIL LINEARITY;64UH,64UH,L-81 OWA 12X15,	
⚠ 3	LX801S	AA29-30002N	FILTER LINE NOISE;-,16MH,1.5A,AC100~260V	
⚠ 3	NT801S	1404-001045	THERMISTOR-NTC;4.7ohm,15%,2900K,35.0mW,T	
⚠ 3	PC801S	0604-001038	PHOTO-COUPLER;TR,130-260%,200mW,DIP-4,ST	
⚠ 3	PT801S	1404-000002	THERMISTOR-PTC;9ohm,20%,-,-,TR,RECT,-	
3	Q401	0502-001136	TR-POWER;KSD5703,NPN,70W,TO-3PF,ST,8-	
3	Q403	AA96-00243F	ASSY H/S;-,VERTICAL,AA62-00045A,IRF620,V	S.N.A
4		0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
4		0505-000156	FET-SILICON;IRF620,N,200V,5A,0.8ohm,50W,	
4		6003-000335	SCREW-TAPTITE;RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
4		AA62-00045A	HEAT SINK-PS;-,-,T1.0,-,-,DREAM,-,-,-,-,	S.N.A
⚠ 3	RL801S	3501-001040	RELAY-POWER;12VDC,500MW,10000MA,1FORMA,1	
⚠ 3	T401	AA26-50001M	TRANS-HORIZ.DRIVE;-,-,-,80mH,-,-,520uH,-	
⚠ 3	T444S	AA26-00057A	TRANS FBT;-,FUH-29A001B(S),25/29,130	
⚠ 3	T801S	AA26-00157B	TRANS SWITCHING;42B130,VC1A,CIS,160V ~30	
⚠ 3	TU01S	AA40-00096A	TUNER;TCLS3101PD16A(N),PAL,181CH,38.9MHZ	
3		AA97-13682A	ASSY AUTO-MAIN;DW21G5VD3X/BWT,VC1A,RUI	S.N.A
4	C101	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
4	C102	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
4	C103	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
4	C104	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C105	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
4	C106	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C107	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	C108	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C251	2201-000611	C-CERAMIC,DISC;0.056NF,5%,50V,C0G,TP,7X3	
4	C301	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C302	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C303	2201-002022	C-CERAMIC,DISC;0.005NF,0.25PF,500V,C0G,T	
4	C304	2305-000285	C-FILM,MPEF;220NF,5%,100V,TP,10.5X5.5X15	
4	C305	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.5	
4	C306	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C307	2401-000360	C-AL;100uF,20%,50V,GP,TP,8x11.5,5	
4	C309	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C401	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C402	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
4	C403	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C404	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
4	C406	2401-002300	C-AL;47uF,20%,50V,GP,TP,6.3x11,5	
4	C407	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	
4	C408	2305-000382	C-FILM,MPEF;4.7nF,5%,400V,TP,-,5mm	
4	C411	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4	C412	2305-000178	C-FILM,MPEF;10nF,5%,100V,TP,-,5mm	
4	C414	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5	
4	C420	2301-001397	C-FILM,PPF;2.2nF,5%,1.2kV,TP,15x8.5x13.5	
4	C421	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.	
4	C422	2401-000927	C-AL;22uF,20%,250V,GP,TP,13x20,5	
4	C424	2201-000132	C-CERAMIC,DISC;0.1NF,10%,500V,Y5P,TP,6.5	
4	C427	2401-002267	C-AL;2.2uF,20%,250V,GP,TP,8x11.5,5	
4	C430	2301-001342	C-FILM,PPF;1.5nF,5%,800V,TP,15x6.5x11.5m	
4	C602	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C603	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C604	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10x20,5mm	
4	C605	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4	C606	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C607	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C608	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C609	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
4	C610	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
4	C611	2401-001914	C-AL;1uF,20%,50V,BP,TP,5x11,5	
4	C620	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	C621	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
4	C622	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4	C703	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
4	C704	2401-001101	C-AL;330uF,20%,16V,GP,TP,8x11.5,5	
4	C711	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
4	C715	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C716	2202-000243	C-CERAMIC,MLC-AXIAL;33pF,5%,50V,SL,TP,3.	
4	C717	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T	
4	C801	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	C802	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C803	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C804	2201-000332	C-CERAMIC,DISC;2.2NF,20%,250V,Y5U,TP,9X4	
4	C805	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4	C807	2301-001435	C-FILM,PPF;1.5nF,5%,1.2kV,TP,15x8x12.5mm	
4	C808	2401-001192	C-AL;33uF,20%,50V,GP,TP,6.3x11,5	
4	C809	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4	C811	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,	
4	C812	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4	C813	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
4	C814	2201-000639	C-CERAMIC,DISC;0.68NF,10%,2KV,Y5P,TP,9X5	

Loc. No.	Code No.	Description ; Specification	Remark
4 C815	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4 C816	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5	
4 C817	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4 C818	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
4 C820	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4 C821	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4 C822	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,5	
4 C824	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4 C826	2401-000025	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
4 C828	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
4 C829	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4 C839	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4 C840	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5	
4 C841	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
4 C843	2201-000374	C-CERAMIC,DISC;0.22NF,5%,50V,C0G,TP,10.5	
4 C844	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
4 C847	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4 C848	2401-002215	C-AL;2200uF,20%,25V,WT,TP,13x25,5	S.N.A
4 C901	2401-000050	C-AL;10uF,20%,16V,GP,TP,5x11,2.5	
4 C902	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm	
4 C903	2401-002463	C-AL;470uF,20%,16V,GP,TP,8x11.5,5	
4 CN501	3711-002647	CONNECTOR-HEADER;BOX,8P,1R,2.5mm,STRAIGH	
4 CN502A	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH	
4 CN602	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH	
⚠ 4 CR403S	2303-001001	C-FILM,PPF;22nF,5%,630V,TP,18x14.5x8.5mm	
4 D102	0403-001373	DIODE-ZENER;MTZJ5.1A,4.81V-5.07V,500mW,D	
4 D301	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D401	0402-000010	DIODE-RECTIFIER;RGP15G,400V,1.5A,DO-204A	
⚠ 4 D402	0402-000010	DIODE-RECTIFIER;RGP15G,400V,1.5A,DO-204A	
⚠ 4 D403	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D405	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D406	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D407	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D410	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D411	0402-000010	DIODE-RECTIFIER;RGP15G,400V,1.5A,DO-204A	
⚠ 4 D413	0402-000010	DIODE-RECTIFIER;RGP15G,400V,1.5A,DO-204A	
⚠ 4 D418	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4 D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
4 D602	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D801	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D802	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D803	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D804	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D807	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
⚠ 4 D808A	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 4 D810	0402-000546	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	
⚠ 4 D811	0404-001056	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	
⚠ 4 D821	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
⚠ 4 D831	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D832	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
⚠ 4 D833	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D834	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D835	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
⚠ 4 D836	0404-000156	DIODE-SCHOTTKY;RB441Q,10V,100mA,DO-34,TP	
4 DE812A	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
4 DZ201	0403-000700	DIODE-ZENER;TZP33A,33V,31-35V,1W,DO-41,T	
4 DZ302	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
4 DZ303	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
4 DZ304	0403-001329	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	
4 DZ305	0403-001221	DIODE-ZENER;UZ39BSB,35.36-37.19V,500MW,D	
4 DZ306	0403-001167	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	
4 DZ701	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4 DZ702	0403-000720	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	
4 DZ801	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
4 DZ802	0403-000716	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	
4 DZ803	0403-001330	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	
4 DZ804	0403-001327	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	
4 DZ805	0403-001322	DIODE-ZENER;MTZJ8.2B,7.78-8.19V,500mW,DO	
4 DZ806	0403-001318	DIODE-ZENER;MTZJ4.3B,4.17-4.43V,500mW,DO	
4 DZ808	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4 DZ810	0403-001211	DIODE-ZENER;MTZJ12B,11.44-12.03V,500MW,D	
4 DZ812	0403-001373	DIODE-ZENER;MTZJ5.1A,4.81V-5.07V,500mW,D	
4 DZ813	0403-000714	DIODE-ZENER;MTZJ3.3B,3.3V,3.32-3.53V,500	
4 DZ814	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4 DZ901	0403-000508	DIODE-ZENER;MTZJ5.6B,5.6V,5.45-5.73V,500	
4 EL01	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL02	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
4 EL03	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL04	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL05	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL06	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL07	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL08	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL10	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL11	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL12	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL13	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL14	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL15	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL19	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EL20	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4 EY01	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY02	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY03	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY04	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY05	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY06	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY07	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY08	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY09	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY10	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY11	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY12	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY13	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY14	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY15	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY16	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY17	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY18	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY19	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY20	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY21	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY22	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY23	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY24	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY26	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY28	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY29	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY30	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY31	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY32	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY33	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY34	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY35	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY36	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY37	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY38	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY39	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY40	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY41	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY42	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY44	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY45	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY46	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY47	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY48	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY49	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY50	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY51	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY52	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY53	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY54	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY55	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY56	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY57	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY58	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY59	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY60	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY61	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY62	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY63	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY64	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY65	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4 EY66	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A

Loc. No.		Code No.	Description ; Specification	Remark
4	EY67	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY68	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY69	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY70	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY71	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY72	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY73	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY74	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY75	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY76	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY77	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY78	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY79	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY80	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY81	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY82	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY83	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY84	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY85	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY86	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY87	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY88	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY89	6042-000001	EYELET;ID2.2,OD2.7,L3.1,SN,BSS3-E/EH	S.N.A
4	EY92	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	EY93	6042-000002	EYELET;ID1.5,OD2,L3.1,SN,BSS3-E/EH	S.N.A
4	F801A	3602-000114	FUSE-HOLDER;-,-,30mohm	
4	F801B	3602-000114	FUSE-HOLDER;-,-,30mohm	
⚠ 4	FA801S	3601-001163	FUSE-AXIAL LEAD;125V,7A,-,EPOXY,2.4X7.1M	
4	GT102	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT103	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT601	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT802	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT803	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT804	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT805	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT806	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	GT811	AA60-40014A	PIN-GT,ASSY;AUTO	S.N.A
4	L101	2701-000115	INDUCTOR-AXIAL;10uH,10%,3x7mm	
4	L102	2701-000116	INDUCTOR-AXIAL;10uH,10%,4.2x9.8mm	
4	L103	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L104	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L205	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L208	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L302	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L303	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L304	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L305	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
⚠ 4	L401	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
4	L601	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L602	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L603	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L606	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L607	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L608	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L701	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L702	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L706	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
4	L707	2901-000299	FILTER-EMI ON BOARD;-,6A,UL/CSA,-,9x7.5,	
4	L708	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L709	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
4	L801	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L802	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
4	L803	3301-001223	CORE-FERRITE BEAD;AA,62ohm,3.5x0.8x5mm,-	
4	L804	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L805	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L806	2901-000297	FILTER-EMI ON BOARD;-,3A,-,-,3.5x5,TP,-	
4	L808	2701-001007	INDUCTOR-AXIAL;24uH,10%,4.5x14mm	
4	L809	3301-000287	CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	
4	L903	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
4	PCB	AA41-00523B	PCB-MAIN;SMD-21G5S,FR-1,1L,B,1.6T,330X24	S.N.A
4	Q402	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
4	Q601	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
4	Q602	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
4	Q701	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q702	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
4	Q801	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q802	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	

Loc. No.		Code No.	Description ; Specification	Remark
4	Q803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL	
4	Q804	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q805	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q806	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
4	Q807	0504-000119	TR-DIGITAL;KSR1004,NPN,300MW,47K/47K,TO-	
4	Q808	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q809	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q810	0501-000362	TR-SMALL SIGNAL;KSA2328A-Y,NPN,1W,TO-92L	
4	Q811	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
4	Q812	0504-000142	TR-DIGITAL;KSR2001,PNP,300MW,4.7K/4.7K,T	
4	R101	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R102	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R103	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R104	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R105	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R106	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R107	2003-000493	R-METAL OXIDE(S);12ohm,5%,2W,AF,TP,4x12m	
4	R301	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
4	R302	2004-001984	R-METAL(S);26.7Kohm,1%,1/2W,AA,TP,2.4x6.	
4	R303	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM	
4	R304	2001-001157	R-CARBON(S);5.6OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R305	2001-001157	R-CARBON(S);5.6OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R306	2003-002157	R-METAL OXIDE;220OHM,5%,2W,AG,TP,6X16MM	
4	R314	2004-001986	R-METAL(S);35.7Kohm,1%,1/2W,AA,TP,2.4x6.	
4	R315	2004-001126	R-METAL;6.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
4	R402	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R403	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R404	2001-000037	R-CARBON(S);330OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R405	2008-000264	R-FUSIBLE(S);1ohm,5%,1W,AF,TP,3.9x10mm	
4	R406	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R408	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
4	R409	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
4	R410	2001-001114	R-CARBON(S);270OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R411	2001-001139	R-CARBON(S);39KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R412	2001-000020	R-CARBON(S);22OHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R415	2001-001078	R-CARBON(S);15KOHM,5%,1/2W,AA,TP,2.4X6.4	
4	R417	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R421	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4	R423	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R424	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
4	R425	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
4	R426	2003-002178	R-METAL OXIDE(S);1Kohm,5%,2W,AG,TP,3.9x1	
4	R429	2004-002016	R-METAL(S);15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
4	R430	2004-004029	R-METAL(S);10Kohm,1%,1/2W,AA,TP,2.5x6.5m	
4	R432	2004-001403	R-METAL(S);7.5Kohm,1%,1/2W,AA,TP,2.4x6.4	
4	R433	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R434	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
4	R435	2008-001018	R-FUSIBLE(S);0.47ohm,10%,2W,AF,TP,3.9x10	
4	R436	2003-002151	R-METAL OXIDE;18KOHM,5%,2W,AG,TP,6X16MM	
4	R441	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R606	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R608	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R609	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R610	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R611	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R612	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R620	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R621	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R622	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R623	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R624	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R625	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R701	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R702	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R703	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R704	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R705	2001-001138	R-CARBON(S);390OHM,5%,1/2W,AA,TP,2.4X6.4	
4	R706	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R707A	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R708	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R709	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R713	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R714	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R716	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R717	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R718	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4	R720	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark
4 R721	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R722	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R723	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R724	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R725	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R726	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R727	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R801	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
4 R802	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
4 R803	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
4 R804	2003-000586	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
4 R805	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4 R806	2001-001150	R-CARBON(S);470KOHM,5%,1/2W,AA,TP,2.4X6.	
4 R807	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
4 R808	2008-000284	R-FUSIBLE(S);0.1OHM,10%,2W,AF,TP,3.9X10M	
4 R810	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
4 R811	2001-001155	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
4 R812	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
4 R813	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R814	2001-000800	R-CARBON;5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R815	2001-001108	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4	
4 R816	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R817	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R818	2001-001131	R-CARBON(S);33KOHM,5%,1/2W,AA,TP,2.4X6.4	
4 R819	2004-001983	R-METAL(S);2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
4 R820	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R821	2004-001889	R-METAL(S);127Kohm,1%,1/2W,AA,TP,2.5x6.5	
4 R822	2003-002020	R-METAL OXIDE(S);56Kohm,5%,2W,AF,TP,3.9x	
4 R823	2001-001079	R-CARBON(S);15OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R824	2008-001011	R-FUSIBLE(S);0.18ohm,10%,2W,AF,TP,3.9x10	
4 R825	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R826	2003-002153	R-METAL OXIDE;4.7OHM,5%,2W,AG,TP,6X16MM	
4 R827	2003-002153	R-METAL OXIDE;4.7OHM,5%,2W,AG,TP,6X16MM	
4 R828	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R829	2001-000577	R-CARBON;2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R833	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R834	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R837	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R842	2001-001077	R-CARBON(S);150OHM,5%,1/2W,AA,TP,2.4X6.4	
4 R843	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R844	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
4 R845	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R846	2008-001087	R-FUSIBLE(S);1.8ohm,5%,2W,AG,TP,3.9x12mm	
4 R847	2001-001116	R-CARBON(S);27OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R849	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R850	2001-001187	R-CARBON(S);75OHM,5%,1/2W,AA,TP,2.4X6.4M	
4 R934	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
4 R935	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
⚠ 4 RX801S	2002-001011	R-COMPOSITION;3.3Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4 RY801S	2002-001012	R-COMPOSITION;8.2Mohm,5%,1/2W,AA,TP,3.7x	
⚠ 4 VP801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
⚠ 4 VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	
3	AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,W	S.N.A
3	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A
3	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
3	0202-000187	SOLDER-WIRE FLUX;-,RS60S,D1.2,63Sn/37Pb	S.N.A
3	AA65-30009A	CLAMPER CORE-FBT;-,ABS,V0,-,BLK,-	S.N.A
2	AA94-12521A	ASSY PCB MISC-M/DECK;DW21G5VD3X/BWT,VC1A	
3 CN002A	AA39-20497D	LEAD CONNECTOR-ASSY;,1P,400MM,YFH800-01,	
3 CND01A	AA39-00282B	LEAD CONNECTOR-ASSY;VC1A,UL2651#28,UL/CS	
3	AA96-01324A	ASSY MISC P-DECK-M/DVDP;DVD-DS002/VD,VC1	S.N.A
3	AA96-01320A	ASSY PCB P-M/DVDP;DVD-PSR25/VD,VC1A,MPEG	
3	AA90-03939A	ASSY COVER MISC;TX14N3DF4X/XEG	S.N.A
4 D/P+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
4 DECK+F	6003-001022	SCREW-TAPTITE;RH,+,B,M3,L12,ZPC(BLK),SWR	S.N.A
4 DVD/P+	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
4 O/P+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
4 SDT+FD	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
4	AA65-00011B	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
4	AA63-00339B	SHIELD-DECK,TOP;21G5,SECC,T0.5,-,-,-,TOP	S.N.A
4	AA61-00596B	FRAME-DECK;28G5,-,-,HIPS V0,BLK,-,-,-,MI	S.N.A
3	3809-001180	CABLE-FLAT;30V,-30to+80C,80mm,35P,1.25mm	
3	3809-001427	CABLE-FLAT;60V,80C,80MM,24P,1MM,UL20624	
3	3809-001426	CABLE-FLAT;60V,80C,80MM,13P,1MM,UL20624	

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY COVER REAR	
1	AA90-02001U	ASSY COVER REAR;21G5,DW21G5VD2X/BWT	S.N.A
2 BACK	AA60-00091A	SPACER-FELT;-,FELT,150X10,-,-,BLK,T0.35,	S.N.A
2	AA65-30008A	CLAMPER CORE-CORD;-,PE,HB,-,BLK,-	S.N.A
2	AA64-01330C	INLAY-BACK,DVD;21G5,PS SHEET,T0.5,-,-,BL	S.N.A
2	AA64-01329C	INLAY-BACK,TV;21G5,PS SHEET,T0.5,-,-,BLK	S.N.A
2	AA64-01322G	CABINET BACK;21G5,HIPS V2,G4309	
		ASSY COVER FRONT	
1	AA90-01838X	ASSY COVER FRONT;21G5,DW21G5V2X/BWT	S.N.A
2 AV+CF	6003-001268	SCREW-TAPTITE;TH,+,B,M4.0,L12.0,ZPC(YEL)	S.N.A
2 CB+CF	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2 CB+FD	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2 DCP+CF	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
2 KPP+CF	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
2 RJ+CB	AA60-10050T	SCREW-TAPPING;-,SWRCH18A,M4,L20,RH,+,2S,	S.N.A
2 SPK+CF	6006-001095	SCREW-ASS'Y TAPT;WP,BH,+,M4,L12,ZPC(YEL)	S.N.A
2 TKC+CF	6002-000522	SCREW-TAPPING;TH,+,2,M4,L15,ZPC(BLK),SWR	
2	AA91-00684A	ASSY HOLDER SPK;-,-,8OHM/5W,-,TVDP VE TY	
2	AA91-00494N	ASSY CABINET FRONT;,21G5,SV012P+DB004P E	
3 CF+KCD	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
3 CF+KCT	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
3 WIN+CF	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	S.N.A
3	AA64-01325B	WINDOW REMOCON;21G5,PC V0,-,-,-,-,VIOLET	S.N.A
3	AA64-01326B	INDICATOR LED;21G5,ACRYL,-,-,-,-,-	
3	AA64-01328B	DECORATION-FRONT;21G5,ABS HB,-,-,-,-,G36	
3	AA64-01572C	KNOB-TV;21G5,ABS,-,-,-,HB,G3676,-,SV012P	
3	AA64-01763B	INLAY-BARRIER,FRONT;21G5,PVC,T0.4,-,-,-	S.N.A
3	AA65-00011C	CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A
3	AA64-70123A	BADGE-BRAND;NEW,AL,-,-,L=50,FLAT,SILVER,	S.N.A
3	AA61-60003J	SPRING ETC-CS;-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A
3	AA64-00846D	INLAY AV;21G5,PS SHEET,T0.3,-,-,BLK,3P E	S.N.A
3	AA64-01321M	CABINET-FRONT;21G5,HIPS,HB,G4309,SV012P+	S.N.A
3	AA64-01323B	KNOB-DVD;21G5,ABS HB,-,-,-,-,G3676,-,SV0	
3	AA64-01324B	KNOB POWER;21G5,ABS HB,-,-,-,-,G3676,-,S	
2	AA65-00009B	CLAMPER CORE-D,COIL;21A8,NYLON 66,V0,-,-	S.N.A
2	AA64-01934A	DOOR-TRAY,ASSY;21G5,ABS HB,G3676,LB017M	
3	AA64-01875B	DOOR-TRAY;21G5,ABS HB,G3676,LB017M	
2	AA60-10050R	SCREW-ASSY;-,SWRCH18A,M5,L31.5,HH,+,WC,-	S.N.A
		ASSY ACCESSORY	
1	AA92-07545A	ASSY ACCESSORY;DW21G5VD3X/BWT,RUSSIA,V	S.N.A
2	AA69-00862A	BAG PE;-,HDPE PE FOAM,T0.03,W400,H240,-	S.N.A
2	AA68-01917C	MANUAL USERS;DW21G5VD,RUS,W/P100(G),B5,C	
2	AA68-01402A	MANUAL-GOOD WILL LETTER;,CIS,B5,1PAGE,A/	S.N.A
2	AA68-01120A	MANUAL SERVICE;-,-,CIS,A4,6PAGE(FOLD),W/	S.N.A
2	AA68-00952A	CARD-COUPON;-,A/P100(G),AA68-00949A,-,-	S.N.A
2	AA68-00816B	CARD WARRANTY-01;,RUSSINA,2,W/P 120G,BOT	S.N.A
2	AA59-00204B	REMOCON;,TM65,TVDP,51,SILVER,S/S,L/GRAY,	
2	6801-001073	CARD-REGISTRATION;RUS,XEV,RUS,MOJO100,-,	S.N.A
		ASSY CPT	
1	AA91-02618A	ASSY CPT;DW21G6VD2X/XEF	S.N.A
2	AA91-02169E	ASSY CPT;A51QDX992X,21,0MG,BARE,AA03-00	S.N.A
3	AA63-60028A	SPACER-DY;-,NEOPRENE,-,-,-,BLK,-,-,V0 W1	S.N.A
3	AA27-00198A	DEFLECTION YOKE;21DF,DIF-2192AA(NF),ST-3	
3	AA27-00002A	MAGNET CONVERGENCE;-,JH291-SC-OB,29.1MM	
⚠ 3	AA03-00317A	CRT COLOR;A51QDX992X,0MG,1.85MH,18.0MH,2	
2	AA98-00011B	ASSY TBC WIRE(P);-,21INCH,PAL,2P,CS-5399	S.N.A
2	AA27-00113A	COIL DEGAUSSING;-,-,4.8mH,-,48T,9ohm,-,2	

Loc. No.	Code No.	Description ; Specification	Remark
		ASSY LABEL	
1	AA92-07396A	ASSY LABEL;DW21G5V2X/BWT,VC1A,RUSSIA	S.N.A
		ASSY BOX	
1	AA92-03849F	ASSY BOX;21G5	S.N.A
		ASSY P/MATERIAL	
1	AA92-03090M	ASSY P/MATERIAL;DW21G5VDX/BWT	S.N.A
2	AA69-00744D	BAG-SHEET;-,HDPE PE FOAM,T0.015,W1200,H1	S.N.A
2	AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
2	AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
2	AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A